

Product datasheet

Specifications



ammeter dial PowerLogic - 1.3 In - ratio 200/5 A

16081

⚠ Discontinued on: 9 Dec 2024

⚠ Discontinued

Main

Range of product	PowerLogic
Product name	AMP
Product or component type	Dial
Current transformer ratio	200/5
Scale type	80 mm over 90°
Mounting support	Front face

Complementary

Type of measurement	Current
Scale	0-200 A

Environment

Height	96 mm
Width	96 mm
Depth	75 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	0.1 cm
Package 1 Width	8.5 cm
Package 1 Length	8.5 cm
Package 1 Weight	12.0 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	7.8 cm
Package 2 Width	11.6 cm
Package 2 Length	11.6 cm
Package 2 Weight	165.0 g
Unit Type of Package 3	S03
Number of Units in Package 3	100

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 3 Height	30.0 cm
Package 3 Width	30.0 cm
Package 3 Length	40.0 cm
Package 3 Weight	2.137 kg

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant By Exemption

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
End of life manual availability	End of Life Information
Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins